

## SP107E Bluetooth LED Music Controller Operating Instructions



### 1.Product features:

- 1.Long distance APP remote control via Bluetooth;
- 2.Support almost every kind of one-wire or two-wires LED driver!
- 3.Support setting pixel number and segment number,support up to 960 pixels;
- 4.With 18 kinds of LED strip music effects, 30 kinds of LED matrix music effects and 180 kinds of non-music effects;
- 5.DC 5V~24V wide range working voltage,reverse power supply input protection;
- 6.User setting saving;Download and install the APP

### 2.Download and install the APP:

Both IOS version and Android IOS version are available.(hardware should support Bluetooth)

1.Requires IOS version 10.0 or later

2.Requires Android OS version 4.4 or later

3.Search "LED Chordin" App Store or GooglePlay or scan this QR code to download and install the APP:



### 3.Instructions:

#### APP Operations:

- 1.Make sure you have turn on Bluetooth on your phone;
- 2.Open the APP,drag to refresh the devicelist,select device name“ SP107E” to connect the controller,once connected you will able to rename your controller.
- 3.Select RGB order and ICtype;
- 4.Adjust pixel number;
- 5.Press **ENTER**.

#### Audio Input:

There are two ways to input the audio signal on SP107E,AUXIN and Build-INmicrophone;

- 1.AUXIN:Plug the supplied audio split cable into the “ **AUXIN**” jack,connect the audio output source(MP3,Phone or tablet..)and the speaker(or headset),controller will automatically switch into AUX input mode;
- 2.MIC:Disconnect the audio cable,controller will automatically switch into microphone input mode.

### 4.specifications:

Working temperature:-20 ~60

;Working Voltage:DC5V~24V

Working Current:18mA~45mA

Remote distance:20Meters

Product size:85mm\*45mm\*22mm

;Product weight:40g

Certificates:CE,RoHS

